

Models Affected	No5802/No5805
Version	1.43

To update via USB:

- Download the firmware file from the product page at MarkLevinson.com or download link you may have received from our Customer Service personnel. Unzip it if necessary and save it to the root folder of a FAT32 formatted USB drive (so they are only files on the stick).
- Turn on the No5805 / 5802
- Insert the stick into the USB socket on the rear of the No5805 / 5802
- Press the MENU button then use the “input” knob and “enter” button to navigate to the following path **SETUP:Advanced→ Firmware→ Update→USB** Wait for the USB stick to be searched
- Wait around 15 minutes, do NOT power off during this time
- The unit will go into standby (blinking red standby light) after completing the upgrade.
- To check your software version, press the MENU button then use the “input” knob and “enter” button to navigate to the following **SETUP:Advanced→ Firmware→ Version** and the display will show: Version 1.41

To update via Ethernet:

- Ensure the No5805 /5802 has a valid internet connection.
- Turn on the No5805 / 5802
- Press the MENU button then use the “input” knob and “enter” button to navigate to the following **SETUP:Advanced→ Firmware→ Update→ ENET** Wait around 15 minutes, do NOT power off during this time.
- The unit will go into standby (blinking red standby light) after completing the upgrade.
- To check your software version, press the MENU button then use the “input” knob and “enter” button to navigate to the following **SETUP:Advanced→ Firmware→ Version** and the display will show: Version 1.41

Version 1.43

Fix list:

3077: Add discovery protocol for use with the 5Kontrol app

3078: Add messaging protocol for use with the 5Kontrol app

3124: SSP volume not handled correctly in all cases when switching back to SSP input (No5805 only)

3136: Fixes power consumption issue in Green Standby